

MIXING CODED SYSTEMS

DAWOUD AHMADI DASTJERDI, MALIHEH DABBAGHIAN AMIRI

ABSTRACT. We show that a coded system is mixing if and only if it is totally transitive and if in addition it has a generator whose length of its elements are relatively prime, then it has strong property P . We continue by showing that a mixing half-synchronized system has such a generator. Moreover, we give an example of a mixing coded system which does not have any generator whose length of its elements are relatively prime.

INTRODUCTION

A coded system X is a subshift over a finite set of alphabet A having a generator set. That is, there exists a countable set of words $\mathcal{W} = \{w_i : w_i \text{ is an admissible word}\}$ called *generator* such that any $x \in X \subseteq A^{\mathbb{Z}}$ is in the closure of the set of arbitrary concatenation of the elements of $\mathcal{W}$. For any coded system there is a graph G with countable vertices and edges that are labeled by the elements of A and so that the closure of recording the labels of all the bi-infinite walks on G determines X [15]. The converse is also true, that is if such a graph exists, then that graph represents a coded system. Coded systems are very chaotic: the periodic points are dense and they are transitive and all have positive entropy.

Subshifts of finite type (SFT) and their factors that is sofic shifts are coded systems and are among the most investigated subshifts. Two known properties of sofics which are of our interest for general case are 1) A sofic system is mixing iff it is totally transitive [2, Theorem 3.3]; 2) A sofic is mixing iff it has a generator $\mathcal{W}$ such that $\gcd(\mathcal{W}) = \gcd(\{|w_i| : w_i \in \mathcal{W}\}) = 1$. We will show that (1) is valid for a general coded system but (2) fails to be so.

The organisation of this paper is as follows. In Section 2, we will give some general results for coded subshifts and as one of our main results, we will prove that a coded subshift is mixing if and only if it is totally transitive. Section 3 is devoted to the properties of those coded systems which have a generator $\mathcal{W}$ such that $\gcd(\mathcal{W}) = \gcd(\{|w_i| : w_i \in \mathcal{W}\}) = 1$. Then we consider a subclass of mixing coded systems with a set of generator $\mathcal{W}$ whose $\gcd(\mathcal{W}) = 1$. We show that this subclass contains the set of half-synchronized systems and all have the strong property P in Section 3.1. So the following implications are satisfied for half-synchronized systems.

$$\begin{aligned} \text{mixing} &\Leftrightarrow \text{strong property } P \Leftrightarrow \\ &K\text{-system} \Leftrightarrow \text{u.p.e.} \Leftrightarrow \text{weak mixing} \Leftrightarrow \text{totally transitive.} \end{aligned}$$

In Section 4, we will construct an example of a mixing coded system whose any generator $\mathcal{W}$ has $\gcd(\mathcal{W}) > 1$.

2010 *Mathematics Subject Classification.* 54H20, 37B10, 37A25.

Key words and phrases. coded system, generator, half-synchronized system.

1. DEFINITIONS AND PRELIMINARIES

A TDS is a pair (X, T) such that X is a compact metric space and T is a homeomorphism. The return time set is defined to be

$$N(U, V) = \{n \in \mathbb{Z} : U \cap T^{-n}V \neq \emptyset\}$$

where U and V are opene (nonempty and open) sets. A TDS (X, T) is *transitive* if $N(U, V) \neq \emptyset$; and it is *totally transitive* if (X, T^n) is transitive for any $n \in \mathbb{Z}$. We call a TDS (X, T) *weak mixing* if $N(U, V)$ is a thick set (i.e. containing arbitrarily long intervals of $\mathbb{Z}$) for any two opene sets U and V ; and is *strong mixing* if $N(U, V)$ is cofinite for opene sets U, V .

Let A be a finite alphabet, i.e. a finite set of symbols. The shift map $\sigma : A^{\mathbb{Z}} \rightarrow A^{\mathbb{Z}}$ is defined by $\sigma((a_i)_{i \in \mathbb{Z}}) = (a_{i+1})_{i \in \mathbb{Z}}$, for $(a_i)_{i \in \mathbb{Z}} \in A^{\mathbb{Z}}$. If $A^{\mathbb{Z}}$ is endowed with the product topology of the discrete topology on A , then σ is a homeomorphism and $(A^{\mathbb{Z}}, \sigma)$ is a TDS called *two-sided shift space*. Similarly, *one-sided shift space* can be defined on $A^{\mathbb{N}_0}$, then σ is a finite-to-one continuous map. A *subshift* is the restriction of σ to any closed non-empty subset Σ of $A^{\mathbb{Z}}$ that is invariant under σ . Set $\sigma_{\Sigma} := \sigma|_{\Sigma}$. A *word (block)* of length n is $a_0 a_1 \cdots a_{n-1} \in A^n$ if there is $x \in \Sigma$ such that $x_i = a_i$, $0 \leq i \leq n-1$. The *language* $\mathcal{L}(\Sigma)$ is the collection of all words of Σ and $\mathcal{L}_n(\Sigma)$ is the collection of all words in Σ of length n . Also, a *cylinder* is defined as $[a_0 \cdots a_n]_p^q = \{x \in \Sigma : x_p = a_0, \dots, x_q = a_n\}$.

Shift spaces described by a finite set of forbidden blocks are called *shifts of finite type* (SFT) and their factors are called *sofic*. A word $w \in \mathcal{L}(\Sigma)$ is called *synchronizing* if whenever $uw, vw \in \mathcal{L}(\Sigma)$, then $uwv \in \mathcal{L}(\Sigma)$. A *synchronized system* is an irreducible shift which has a synchronizing word. A subshift Σ is specified, or has specification property, if there is $N \in \mathbb{N}$ such that if $u, v \in \mathcal{L}(\Sigma)$, then there is w of length N so that $uwv \in \mathcal{L}(\Sigma)$. A specified system is mixing and synchronized and any mixing sofic is specified.

2. GENERAL RESULTS IN CODED SYSTEMS

The coded systems were first defined by Blanchard and Hansel in [5] as an extension for sofic systems. There are several equivalent definitions and we choose the following.

Definition 2.1. A shift space is *coded* if its language $\mathcal{L}$ is freely generated by concatenating words in a countable set $\mathcal{W}$ called the *generator set*. We denote a coded space X by $X(\mathcal{W})$.

A well studied sub-class containing sofics are synchronized systems. The following result was already known for sofics [2, Theorem 3.3] and then extended for synchronized systems [19, Proposition 4.8].

Theorem 2.2. *A coded system is mixing if and only if it is totally transitive.*

Proof. The necessity is clear. So let X , our coding system, be totally transitive. Since a coded system has a dense set of periodic points, X is weak mixing [10, Corollary 3.6].

Let $\mathcal{W}$ be the generator of X and $\gcd(\mathcal{W}) = k$. First assume that there is $u_0 \in \mathcal{W}$ such that $|u_0| = k$.

To see that X is mixing, it suffices to show that for any $u, v \in \mathcal{W}$, $N([u], [v])$ is cofinite. We do this by showing that there exists some $m \in \mathbb{N}$ such that $N([u], [v]) -$

$|u| \supset k\mathbb{N} \cup (k\mathbb{N} + mk + 1) \cup \dots \cup (k\mathbb{N} + mk + k - 1)$. As a result, $N([u], [v]) - |u|$ will contain all numbers greater than $(m + 1)k$ and so it is cofinite.

Since $u_0, u, v \in \mathcal{W}$, for any n we have $u(u_0)^n v \in \mathcal{L}(X)$ and this implies that $k\mathbb{N} \subset N([u], [v]) - |u|$. But X is weak mixing and $N([v], [u])$ must be thick. Hence there does exist some $s \in \mathbb{N}$ such that $s - 1, s - 2, \dots, s - k \in N([v], [u]) - |v|$. This means that $u\alpha_i v \in \mathcal{L}(X)$ where $|\alpha_i| = s - i$.

Observe that for any i , $u\alpha_i v$ is a subword of

$$(2.1) \quad w_i = u_i u \alpha_i v v_i$$

where w_i is constructed by some concatenation of some words in $\mathcal{W}$. By the fact that $\gcd(\mathcal{W}) = k$, $|w_i|, |u|, |v| \in k\mathbb{N}$ and this implies that $|u_i| + |v_i| + s - i \in k\mathbb{N}$. Without loss of generality assume that $s \in k\mathbb{N}$. Hence $|u_i| + |v_i| \equiv i \pmod{k}$ and so there is $m_i \in \mathbb{N}$ such that $|u_i| + |v_i| = m_i k + i$. By considering (2.1), for any $n \in \mathbb{N}$, $vv_i(u_0)^n u_i u \in \mathcal{L}(X)$ and this in turn implies that $nk + m_i k + i \in N([u], [v]) - |u|$.

Since n is arbitrary, by setting $m = \max\{m_1, \dots, m_k\}$, for any i we have $k\mathbb{N} + mk + i \in N([u], [v]) - |u|$.

Now suppose for some $l > 1$, $|u_0| = lk$. Replace u and v with u^l and v^l respectively and we consider w_i^l instead of w_i . So $|u|, |v|, |w_i|$ are in $lk\mathbb{N}$ and by a similar reasoning as above we are done. $\square$

3. MIXING CODED SYSTEMS WITH A RELATIVELY PRIME GENERATOR

A generator $\mathcal{W}$ is called *relatively prime* if $\gcd\{|w_i| : w_i \in \mathcal{W}\} = 1$. Note that if a coded system has a relatively prime generator, then it possesses a generator $\mathcal{W}'$ having two elements with coprime lengths. For there is sufficiently large $k \in \mathbb{N}$ such that $\gcd(\{|w_1|, \dots, |w_k|\}) = 1$. By Bézout's identity and a reindexing of $\{w_1, \dots, w_k\}$ if necessary, there are $y_i \in \mathbb{N}$ with $1 = y_1|w_1| + \dots + y_\ell|w_\ell| - (y_{\ell+1}|w_{\ell+1}| + \dots + y_k|w_k|)$. Now, $\gcd(y_1|w_1| + \dots + y_\ell|w_\ell|, y_{\ell+1}|w_{\ell+1}| + \dots + y_k|w_k|) = 1$ and so we may set

$$\mathcal{W}' = \mathcal{W} \cup \{w_1^{y_1} \dots w_\ell^{y_\ell}, w_{\ell+1}^{y_{\ell+1}} \dots w_k^{y_k}\}.$$

Henceforth, without loss of generality, we may assume that any relatively prime generator has two elements with coprime lengths.

An easy implication of the following lemma is that a coded system with a relatively prime generator is mixing.

Lemma 3.1. *Suppose $\gcd\{a_1, a_2\} = 1$, $a_1, a_2 \in \mathbb{N}$. Then there is $L \in \mathbb{N}$ such that for any $n \geq L$, there are $r_1, r_2 \in \mathbb{N}_0 = \mathbb{N} \cup \{0\}$ with $n = r_1 a_1 + r_2 a_2$.*

Later in Theorem 4.1, we will show that there are examples of mixing coded systems which do not have any relatively prime generator. However, a trivial argument shows that all mixing synchronized do have a relatively prime generator. In order to see this, consider

$$(3.1) \quad \mathcal{W} = \{w\alpha : \alpha w\alpha \in \mathcal{L}(X), \alpha \not\subset w\}$$

as a generator for X where α is a synchronized word; then the assertion follows from the fact that $N([\alpha], [\alpha])$ is cofinite.

A TDS (X, T) is said to have *strong property P* [11, Definition 6.2], if for any finite open sets $U_1, U_2, \dots, U_n$ in X there exists $N \in \mathbb{N}$ such that for any $k \geq 2$ and any $s = (s(1), s(2), \dots, s(k)) \in \{1, 2, \dots, n\}^k$ there exists $x \in X$ with

$$(3.2) \quad x \in U_{s(1)} \cap T^{-N} U_{s(2)} \cap \dots \cap T^{-(k-1)N} U_{s(k)}.$$

Clearly a TDS with specification property has strong property P . The converse is not true though. In fact, Blanchard in [4, Example 5] gives an example of a subshift which has u.p.e but not mixing; so it cannot have specification property. By [4, Proposition 4], Blanchard's example has strong property P . A consequence of this argument is that mixing in a general TDS is different from having property P and does not imply this property. However, a TDS with property P is always weak mixing [4]. The situation is different for a coded system with a relatively prime generator.

Theorem 3.2. *A coded system with a relatively prime generator has strong property P .*

Proof. Let X be mixing coded and $\mathcal{W}$ a generator for X with $\gcd(\mathcal{W}) = 1$. First assume that $v^{(1)}$ and $v^{(2)}$ are two words in $\mathcal{W}$ with coprime lengths. Since any concatenation of $v^{(1)}$ and $v^{(2)}$ is again in $\mathcal{L}(X)$, by Lemma 3.1, there is $L \in \mathbb{N}$ such that for $m \geq L$ there are some concatenations of $v^{(1)}$ and $v^{(2)}$ of length m .

To show that X has strong property P , let $\mathcal{U} = (U_1, \dots, U_n)$ be an n -tuple of nonempty open sets and pick $u_i \in \mathcal{L}(X)$ such that $[u_i] \subset U_i$. Moreover, as a coded system there is $V^{(i)}$ a concatenation of some words in $\mathcal{W}$ such that $u_i \subseteq V^{(i)}$ and let $V^{(i)} = v_i u_i w_i$. We may further assume that there are l and N such that for all i , (1) $l = |v_i|$ and (2) $N = |V^{(i)}|$. This is possible for otherwise set $l' = L + N_0$ where $N_0 = \max\{|v_i| : 1 \leq i \leq k\}$ and extend each $V^{(i)}$ from left by concatenation of some $v^{(1)}$ and $v^{(2)}$ whose sum of lengths is $l' - |v_i|$ and call it $V^{(i)}$ again. This sets (1) and similar reasoning by adding necessary concatenation of $v^{(1)}$ and $v^{(2)}$ from right achieves (2). Observe that by this construction, the concatenation of any order of $V^{(i)}$'s is a word in X and since u_i starts from entry $(l+1)$ of $V^{(i)}$, we have

$$[u_{s(1)}] \cap \sigma^{-N}[u_{s(2)}] \cap \dots \cap \sigma^{-(k-1)N}[u_{s(k)}] \neq \emptyset$$

where $s = (s(1), s(2), \dots, s(k)) \in \{1, 2, \dots, n\}^k$. By allowing $T = \sigma$, this implies that there exists $x \in X$ such that (3.2) is satisfied. $\square$

By [11, Lemma 6.3], any system with strong property P is K -system. In fact, we have the following implications

$$\text{strong property } P \Rightarrow K\text{-system} \Rightarrow \text{u.p.e.} \Rightarrow \text{weak mixing} \Rightarrow \text{totally transitive.}$$

By the above results, all the converses are true for the coded systems with a relatively prime generator.

3.1. Mixing half-synchronized systems. As we saw all mixing synchronized systems have a relatively prime generator. We extend this result to half-synchronized systems. First let us recall the necessary definitions.

For any $x \in X$, $x_- = x_{(-\infty, 0]}$ (resp. $x_+ = x_{(0, \infty)}$) is called a *left ray* (resp. *right ray*). Set $X^- = \{x_- : x \in X\}$ and $X^+ = \{x_+ : x \in X\}$. It is obvious that for any $u \in \mathcal{L}(X)$ and any left (resp. right) ray $x_- \in X^-$ (resp. $x_+ \in X^+$), $x_- u$ (resp. $u x_+$) is a left (resp. right) ray.

Let η be either a word or a left ray. The *follower set* of η is defined as $\omega_+(\eta) = \{x_+ \in X^+ : \eta x_+ \text{ is admissible}\}$. The *follower block* of η is denoted by $F_+(\eta) = \{u \in \mathcal{L}(X) : \eta u \text{ is admissible}\}$. Similarly one may define the *predecessor set* $\omega_-(\zeta)$ or *predecessor block* $F_-(\zeta)$ of a word or a right ray ζ .

Definition 3.3. [7, Definition 0.9] A transitive subshift X is *half-synchronized* if there is $m \in \mathcal{L}(X)$, called the *half-synchronizing* word of X , and a left transitive ray $x_- \in X$ such that $x_{-|m|+1} \cdots x_0 = m$ and $\omega_+(x_-) = \omega_+(m)$.

One can change the condition $F_+(x_-) = F_+(m)$ with $\omega_+(x_-) = \omega_+(m)$ in Definition 3.3. Also, similar definition for a right transitive ray can be given.

Theorem 3.4. *A half-synchronized system is mixing if and only if it has a relatively prime generator.*

Proof. The sufficiency is obviously true. To prove the necessity, we first define a generator $\mathcal{W}$ for a given half-synchronizing system and we will show that if the system is mixing, then $\mathcal{W}$ is relatively prime. Let (X, σ) be a half-synchronized system and let x and m be as provided in Definition 3.3. Define

$$(3.3) \quad \mathcal{W} = \{wm : mwm = x_{-n} \cdots x_0 \subset x_{(-\infty, 0]} \text{ for some } n\}.$$

Since x is left transitive, all words of $\mathcal{L}(X)$ appear infinitely many times as a subword in x_- , in other words, $\mathcal{L}(X) \subseteq \mathcal{L}(\Sigma(\mathcal{W}))$.

We prove our assertion by showing that $\mathcal{L}(\Sigma(\mathcal{W})) \subseteq \mathcal{L}(X)$. This is done by an induction argument for showing that all concatenations of members of $\mathcal{W}$ are in $\mathcal{L}(X)$. It is trivially true for any two concatenations. So assume that this is true for $k-1$ concatenations and consider a k concatenations of members of $\mathcal{W}$ such as $w_{i_1}mw_{i_2}m \cdots w_{i_k}m$. By assumption $m w_{i_2}m \cdots w_{i_k}m$ is admissible; so $w_{i_2}m \cdots w_{i_k}m \in \omega_+(m) = \omega_+(x_-)$. But w_{i_1} appears as a subword in the end of x_- , thus we have $w_{i_1}mw_{i_2}m \cdots w_{i_k}m \in \mathcal{L}(X)$ and so $\mathcal{L}(\Sigma(\mathcal{W})) \subseteq \mathcal{L}(X)$ as required.

Now suppose that X is mixing and assume $\gcd(\mathcal{W}) = k \geq 2$. So for $wm \in \mathcal{W}$,

$$(3.4) \quad |wm| \in k\mathbb{N}.$$

But $N([m], [m])$ is cofinite; so for a fixed $1 \leq i \leq k-1$, there is $u_i \in \mathcal{L}(X)$ such that $mu_i m \in \mathcal{L}(X)$ and $|u_i m| \in k\mathbb{N} + i$. By left transitivity of x , there is some $t_i \in \mathbb{N}$ such that $mu_i m = x_{-t_i} \cdots x_{-t_i+|mu_i m|}$. On the other hand, definition of $\mathcal{W}$ implies that there are some $v_i \in \mathcal{L}(X)$ so that $v_i m, u_i m v_i m \in \mathcal{W}$ and from (3.4), both $|v_i m|$ and so $|u_i m v_i m|$ must be in $k\mathbb{N}$. However, $|u_i m v_i m| = |u_i m| + |v_i m| \in k\mathbb{N} + i$ and so our assumption is false and $k = 1$ as required. $\square$

Corollary 3.5. *A half-synchronized system is mixing if and only if it has strong property P.*

Proof. A system with strong property P is weakly mixing and thus totally transitive and in fact mixing by Theorem 2.2. The converse follows from Theorem 3.4 and Theorem 3.2. $\square$

The generator given in (3.1) is a handy one for synchronized systems. For a half-synchronized system we have:

Theorem 3.6. *Fix a word m and let $\mathcal{U}$ be the collection of all words such that whenever $u = u_1 m u_2 \in \mathcal{U}$, we have $u_2 \in \mathcal{U}$. Set $\mathcal{W} = \{um : u \in \mathcal{U}\}$; then $X = X(\mathcal{W})$ is half-synchronized with a half-synchronizing word m .*

Proof. Choose a left transitive point x_- which is a concatenation of words in $\mathcal{W}$. Thus $x_{[-|m|+1 \dots 0]} = m$ and we have $\omega_+(x_-) \subset \omega_+(m)$. On the other hand, since any concatenation of $\mathcal{W}$ follows x_- , $\omega_+(m) \subset \omega_+(x_-)$ and consequently $\omega_+(m) = \omega_+(x_-)$. $\square$

The converse to the above theorem is also correct, that is, if m is a half-synchronizing word, then there is $\mathcal{U}$ satisfying the hypothesis of the above theorem. For let X be half-synchronized and $\mathcal{W}$ its generator as (3.3). Now this generator is the same as the one provided in Theorem 3.6 by letting $\mathcal{U} = \{w : wm \in \mathcal{W}\}$.

Note that we are not assuming that whenever $u = u_1mu_2 \in \mathcal{U}$, then $u_1 \in \mathcal{U}$. Hence, using Theorem 3.6, one can construct examples of *strictly half-synchronized* system, that is systems which are half-synchronized but not synchronized.

4. CODED MIXING SYSTEMS WITHOUT RELATIVELY PRIME GENERATOR

We give a collection of examples of coded mixing systems without any relatively prime generator.

Theorem 4.1. *For any $k \in \mathbb{N}$ there is a coded mixing system such that if $\mathcal{W}$ is any generator, then $\gcd(\mathcal{W}) \geq k \geq 2$.*

Proof. Assume that $k = 2$ and choose X to be a non-trivial two sided mixing minimal subshift in $\{0, 1\}^{\mathbb{Z}}$ and let $x = \{x_b\}_{b \in \mathbb{Z}} \in X$. Let $S \subset \{0, 1, 2, 3\}^{\mathbb{Z}}$ be the coded system given by the cover $\mathcal{G}$ in Figure 1 where $y_b = x_b + 2$. Denote by π_u a path labeled $u = u_0u_1 \cdots u_{|u|-1}$ in $\mathcal{G}$ and let m_u (resp. M_u) be the integer assigned to the most left (resp. right) vertex appearing in $\mathcal{G}$ for π_u including the initial and terminal vertices. For instance, $\pi_{x_0x_1y_1}$ in Figure 1 has $m_{x_0x_1y_1} = 0$ and $M_{x_0x_1y_1} = 2$. Set $\pi_{x(u)}$ to be the path labeled $x(u) = x_{m_u}x_{m_u+1} \cdots x_{(M_u-1)} \in \mathcal{L}(X)$ initiating at m_u . Observe that $\{y_b\}_{b \in \mathbb{Z}}$ with obvious correction on indices defines a minimal subshift $Y \subset \{2, 3\}^{\mathbb{Z}}$ conjugate to σ_X^{-1} . Let $y(u) = y_{(M_u-1)}y_{(M_u-2)} \cdots y_{m_u} \in \mathcal{L}(Y)$ and note that $x(u)$ and $y(u)$ are not necessarily subwords of u , but if π_u and $\pi_{u'}$ are different paths both labeled by u , then

$$(4.1) \quad x(u) = x(u') \quad \text{and} \quad y(u) = y(u').$$

First, we show that S is mixing. Let $u, u' \in \mathcal{L}(S)$ and by necessary prolongations,




FIGURE 1. Cover $\mathcal{G}$ for S .

we may assume that if π_u (resp. $\pi_{u'}$) is a path labeled u (resp. u'), then π_u (resp. $\pi_{u'}$) starts at m_u (resp. $m_{u'}$) and terminates at M_u (resp. $M_{u'}$), or in fact, $t(\pi_u) = \tau_{x_{(M_u)-1}}$ (resp. $i(\pi_{u'}) = i_{u'_m}$). Since X is mixing, there exists K and paths labeled $w_i \in \mathcal{L}(X)$, $|w_i| \in \{K, K+1, \dots\}$ in $\mathcal{G}$ so that $\pi_{uw_iu'}$ is again a path in $\mathcal{G}$. This means $uw_iu' \in \mathcal{L}(S)$ or equivalently S is mixing.

Now we show that if $\mathcal{W} = \{w_0, w_1, \dots\}$ is any generator for S , then $\gcd(\mathcal{W}) \geq 2$. Since $w_i^\infty \in S$, we do this by showing that if u^∞ is any periodic point in S , then π_u is a cycle in $\mathcal{G}$ and so $|u|$ as well as $|w_i|$ are even numbers. In particular, by assuming u being in its least period ($(u_1 \subseteq u, u_1^\infty = u^\infty) \Rightarrow u_1 = u$), then $|(x(u))^\ell| = |x(u)|$ is constant for all ℓ .

If $u^\infty \in S$ is not the image of any closed cycle in $\mathcal{G}$, then for some sufficiently large ℓ_0 and for all $\ell \geq \ell_0$, there is a path π_{u^ℓ} in $\mathcal{G}$ with $\sup\{|x(u^\ell)| : \ell \geq \ell_0\} = \infty$. By choosing an appropriate subsequence, we may assume that $\lim_\ell |x(u^\ell)| \nearrow \infty$.

Without loss of generality assume that π_u starts at its respective m_u and u is in its least period. By these assumptions, $x(uu) = x(u)x(u)$ and so $x(u^\ell)$ is a word in X for $\ell \geq \ell_0$. This in turn means that X has to have a periodic point $x(u)^\infty$ which is absurd for a minimal system such as X .

Now for an arbitrary $k \geq 2$, let X be as above, but $\{x_i\}_{i \in \mathbb{Z}}$ the orbit of a point $x \in X$ under σ_X^{k-1} . $\square$

Note that any half-synchronized subsystem of S in the above theorem is not mixing. In particular, one can choose non-mixing increasing SFT's $X_1 \subset X_2 \subset \dots$ such that $X = \overline{\bigcup_{i \in \mathbb{N}} X_i}$. That establishes an example of non-mixing SFT's converging to a mixing coded system. See also [19, Example 4.11], for non-mixing SFT's approximating a two sided full shift.

Also, it is not hard to see that the examples of Theorem 4.1 all have strong property P. So the converse of Theorem 3.2 is not necessary true.

REFERENCES

- [1] D. Ahmadi and M. Dabbaghian, *Characterization of spacing shifts with positive topological entropy*, Acta Math. Univ. Comenianae, Vol. LXXXI, 2 (2012), 221–226.
- [2] J. Banks, T. T. D. Nguyen, P. Oprocha, B. Stanley and B. Trott, *Dynamics of spacing shifts*, American Institute of Mathematical Sciences, **33**(9), (2013), 4207–4232.
- [3] V. Bergelson, N. Hindman and R. McCutchen, *Notions of size and combinatorial properties of quotient sets in semigroups*, Topology Proceedings, Vol. **23**, (1998), 23–60.
- [4] F. Blanchard, *Fully positive topological entropy and topological mixing*, Contemp. Math. **135**, (1992), 95–105.
- [5] F. Blanchard, G. Hansel, *Systèmes codés*, Theoret. Computer Sci., **44**, (1986), 17–49.
- [6] F. Blanchard, A. Maass, *Topics in symbolic dynamics and applications*, Cambridge University Press, (2000).
- [7] D. Fiebig and U. Fiebig, *Covers for coded systems*, Contemporary Mathematics, **135**, (1992), 139–179.
- [8] S. Hong and S. Shin, *The entropies and periods of renewal systems*, Israel Journal of Mathematics **172**, (2009), pp. 9–27.
- [9] W. Huang and X. Ye, *A Local variational relation and applications*, Israel Journal of Mathematics **151**, (2006), 237–279.
- [10] W. Huang and X. Ye, *Dynamical systems disjoint from any minimal system*, Transactions of the American Mathematical Society **357** 2, (2004), 669–694.
- [11] W. Huang and X. Ye, *Topological complexity, return times and weak disjointness*, Ergod. Th. & Dynam. Sys. **24**, (2004), 825–846.
- [12] D. Kwietniak, *Topological entropy and distributional chaos in hereditary shifts with applications to spacing shifts and beta shifts*, Discrete Contin. Dyn. Syst, no. 6 (2013), 2451–2467.
- [13] D. Kwietniak and P. Oprocha, *A note on the average shadowing property for expansive maps*, Topology and its Applications, **159**, (2011), 19–27.
- [14] K. Lau, A. Zame, *On weak mixing of cascades*, Math. Systems Theory **6**, (1973), 307–311.
- [15] D. Lind and B. Marcus, *An introduction to symbolic dynamics and coding*, Cambridge Univ. Press, (1995).
- [16] R. McCutcheon, *Three results in recurrence*, Ergodic Theory and its Connections with Harmonic Analysis (Alexandria, 1993), 349–358, London Math. Soc. Lecture Note Ser., **205**, Cambridge Univ. Press, Cambridge, (1995).
- [17] K. Petersen, *On the topological entropy of saturated sets*, Ergodic Theory Dynam. Systems, **27**, (2007), 929–956.
- [18] K. Sigmund, *On dynamical systems with the specification property*, Transactions of the American Mathematical Society **190**, (1974), 285–299.
- [19] T.K. Subrahmonian Moothathu and P. Oprocha, *Syndetic proximality and scrambled sets*, arXiv:1108.1280v4.
- [20] P. Walters, *On the pseudo orbit tracing property and its relationship to stability*, Lecture Notes in Mathematics, **668**, Springer-Verlag, (1987), 231–244.

E-mail address: dahmadi1387@gmail.com, maliheh.dabbaghian@gmail.com